

Programmvorschrift für
Kanalbegrenzungs-PROM MM1 6300-1N

PROM-INPUT A0 A1 A2 A3 A4 A5 A6 A7									PROM OUTPUT Q ₀
Channel No.	PROGRAM CODE								PIN12
	D1 (1F)	D2 (1A)	D3 (1G)	D4 (1E)	D5 (1B)	D6 (2C)	D7 (2A)	D8 (2F)	
1	1	1	1	1	0	1	1	1	1
2	1	0	0	0	0	1	1	1	1
3	1	0	0	1	0	1	1	1	1
4	0	1	0	1	0	1	1	1	1
5	0	0	0	1	1	1	1	1	1
6	0	0	0	0	1	1	1	1	1
7	1	0	1	1	0	1	1	1	1
8	0	0	0	0	0	1	1	1	1
9	0	0	0	1	0	1	1	1	1
10	0	0	1	0	0	0	1	1	1
11	1	1	1	1	0	0	1	1	1
12	1	0	0	0	0	0	1	1	1
13	1	0	0	1	0	0	1	1	1
14	0	1	0	1	0	0	1	1	1
15	0	0	0	1	1	0	1	1	1
16	0	0	0	0	1	0	1	1	1
17	1	0	1	1	0	0	1	1	1
18	0	0	0	0	0	0	1	1	1
19	0	0	0	1	0	0	1	1	1
20	0	0	1	0	0	1	0	1	1
21	1	1	1	1	0	1	0	1	1
22	1	0	0	0	0	1	0	1	1
23	1	0	0	1	0	1	0	1	1
24	0	1	0	1	0	1	0	1	1
25	0	0	0	1	1	1	0	1	1
26	0	0	0	0	1	1	0	1	1
27	1	0	1	1	0	1	0	1	1
28	0	0	0	0	0	1	0	1	1
29	0	0	0	1	0	1	0	1	1
30	0	0	1	0	0	0	0	1	1
31	1	1	1	1	0	0	0	1	1
32	1	0	0	0	0	0	0	1	1
33	1	0	0	1	0	0	0	1	1
34	0	1	0	1	0	0	0	1	1
35	0	0	0	1	1	0	0	1	1
36	0	0	0	0	1	0	0	1	1
37	1	0	1	1	0	0	0	1	1
38	0	0	0	0	0	0	0	1	1
39	0	0	0	1	0	0	0	1	1
40	0	0	1	0	0	0	1	0	1

"1" : logical high level
"0" : logical low level